

OM

SERIES

Quarter-turn

Electric Valve Actuators

(100V, 200V)

The logo for Sun Yeh, featuring a stylized green 'S' followed by the word 'SUNYEH' in blue. The 'Y' and 'E' are connected, and the 'H' has a white arrow pointing to the right.

Electrical Data



SUN YEH ELECTRICAL IND. CO., LTD.

SY01-Ga02A1-EN

Content

1. OM-1 to 9, 1 PH, Class A, B, C.....	1
1.1 100VAC, Floating Control, Class A, B.....	1
1.2 100VAC, Floating Control, Class A+, B+	1
1.3 100VAC, Modulating Control, Class C.....	2
1.4 200VAC, Floating Control, Class A, B.....	2
1.5 200VAC, Floating Control, Class A+, B+	3
1.6 200VAC, Modulating Control, Class C.....	3

Quarter-turn Electric Valve Actuators (100V, 200V) Electrical Data

1. OM-1 to 9, 1 PH, Class A, B, C

1.1 100VAC, Floating Control, Class A, B

Model	Torque		Motor Power W	Power Consumption DC / 60 / 50 Hz W	Duty Performance		Running Current 60 / 50 Hz Amp	Running Time 60 / 50 Hz Sec / 90°	Start Current 60 / 50 Hz Amp	Lock Current 60 / 50 Hz Amp
	Nm	in-lb			Cycles / hour	Starts / hour				
OM-2	90	800	40	180 / 160	15	120	1.8 / 1.6	16 / 19	5 / 5	2.3 / 2.5
OM-3	150	1330	40	170 / 150	10	60	1.7 / 1.5	25 / 30	5 / 5	2.3 / 2.5
OM-H	300	2655	60	200 / 200	10	60	2.0 / 2.1	24 / 28	7 / 7	3.9 / 4.2
OM-4	400	3540	80	220 / 270	10	60	2.2 / 3.0	19 / 22	8 / 8	4.9 / 5.2
OM-5	500	4430	80	220 / 260	10	60	2.2 / 2.9	25 / 30	8 / 8	4.9 / 5.2
OM-6	650	5755	80	220 / 260	10	60	2.2 / 2.9	31 / 37	8 / 9	4.9 / 5.2
OM-7	1050	9300	120	260 / 280	5	30	2.6 / 3.3	51 / 60	13 / 13	7.2 / 7.7
OM-8	1500	13280	120	310 / 290	5	30	3.1 / 3.3	53 / 62	12 / 12	7.2 / 7.7
OM-9	2000	17710	180	360 / 340	5	30	3.8 / 3.9	59 / 71	22 / 22	13.6 / 14.8

- The running current is measured at max torque.

1.2 100VAC, Floating Control, Class A+, B+

Model	Torque		Motor Power W	Power Consumption DC / 60 / 50 Hz W	Duty Performance		Running Current 60 / 50 Hz Amp	Running Time 60 / 50 Hz Sec / 90°	Start Current 60 / 50 Hz Amp	Lock Current DC Amp
	Nm	in-lb			Cycles / hour	Starts / hour				
OM-1	35	310	10	40 / 40	30	240	0.6 / 0.6	15 / 15	3 / 3	1.8
OM-A / AM	50	445	10	40 / 40	30	240	0.5 / 0.5	23 / 24	3 / 3	1.8
OM-2	90	800	40	60 / 60	30	240	0.7 / 0.7	15 / 15	5 / 5	4.8
OM-3	150	1330	40	60 / 60	20	120	0.7 / 0.7	23 / 22	5 / 5	4.8
OM-H	300	2655	60	100 / 100	20	120	1.1 / 1.2	21 / 21	6 / 6	5.4
OM-4	400	3540	80	210 / 230	20	120	2.6 / 2.8	17 / 17	12 / 13	14.3
OM-5	500	4430	80	180 / 210	20	120	2.2 / 2.5	22 / 23	12 / 12	14.3
OM-6	650	5755	80	170 / 180	20	120	2.1 / 2.2	28 / 28	12 / 12	14.3
OM-7	1050	9300	120	210 / 210	10	60	2.5 / 2.5	42 / 41	12 / 13	15.9
OM-8	1500	13280	120	260 / 280	10	60	3.1 / 3.3	46 / 46	12 / 13	15.9
OM-9	2000	17710	180	280 / 280	10	60	3.4 / 3.4	70 / 68	13 / 13	16.6

- The running current is measured at max torque.

Quarter-turn Electric Valve Actuators (100V, 200V) Electrical Data

1.3 100VAC, Modulating Control, Class C

Model	Torque		Motor Power	Power Consumption DC / 60 / 50 Hz	Duty Performance	Running Current 60 / 50 Hz	Running Time 60 / 50 Hz	Start Current 60 / 50 Hz	Lock Current DC
	Nm	in-lb	W	W	Starts / hour	Amp	Sec / 90°	Amp	Amp
OM-1	35	310	10	50 / 50	1200	0.7 / 0.7	14 / 14	- *	1.8
OM-A / AM	50	445	10	40 / 40	1200	0.6 / 0.5	25 / 24	- *	1.8
OM-2	90	800	40	70 / 70	1200	0.8 / 0.8	15 / 15	5 / 5	4.8
OM-3	150	1330	40	60 / 60	600	0.7 / 0.7	23 / 22	5 / 5	4.8
OM-H	300	2655	60	100 / 110	600	1.1 / 1.2	23 / 22	6 / 6	5.4
OM-4	400	3540	80	180 / 190	600	2.1 / 2.3	16 / 16	13 / 13	14.3
OM-5	500	4430	80	180 / 200	600	2.2 / 2.5	23 / 22	12 / 12	14.3
OM-6	650	5755	80	170 / 180	600	2.1 / 2.2	28 / 28	12 / 13	14.3
OM-7	1050	9300	120	210 / 210	300	2.5 / 2.5	42 / 41	12 / 13	15.9
OM-8	1500	13280	120	260 / 270	300	3.1 / 3.2	47 / 45	13 / 13	15.9
OM-9	2000	17710	180	270 / 280	300	3.3 / 3.3	70 / 67	14 / 13	16.6

- The running current is measured at max torque.

* The start current of SY-H215101 is soft start mode, the start current is lower than running current.

1.4 200VAC, Floating Control, Class A, B

Model	Torque		Motor Power	Power Consumption DC / 60 / 50 Hz	Duty Performance		Running Current 60 / 50 Hz	Running Time 60 / 50 Hz	Start Current 60 / 50 Hz	Lock Current 60 / 50 Hz
	Nm	in-lb	W	W	Cycles / hour	Starts / hour	Amp	Sec / 90°	Amp	Amp
OM-2	90	800	40	200 / 160	15	120	1.0 / 0.8	16 / 19	2 / 3	1.2 / 1.2
OM-3	150	1330	40	200 / 160	10	60	1.0 / 0.8	25 / 30	3 / 3	1.2 / 1.2
OM-H	300	2655	60	210 / 160	10	60	1.1 / 0.8	24 / 28	3 / 3	1.5 / 1.5
OM-4	400	3540	80	320 / 240	10	60	1.7 / 1.2	18 / 22	4 / 4	2.4 / 2.4
OM-5	500	4430	80	320 / 260	10	60	1.7 / 1.3	26 / 30	4 / 4	2.4 / 2.4
OM-6	650	5755	80	300 / 240	10	60	1.6 / 1.2	31 / 37	4 / 4	2.4 / 2.4
OM-7	1050	9300	120	300 / 270	5	30	1.5 / 1.5	51 / 60	6 / 6	3.5 / 3.7
OM-8	1500	13280	120	330 / 300	5	30	1.7 / 1.6	51 / 61	6 / 6	3.5 / 3.7
OM-9	2000	17710	180	350 / 290	5	30	2.1 / 1.5	58 / 70	10 / 11	6.0 / 6.7

- The running current is measured at max torque.

Quarter-turn Electric Valve Actuators (100V, 200V) Electrical Data

1.5 200VAC, Floating Control, Class A+, B+

Model	Torque		Motor Power W	Power Consumption DC / 60 / 50 Hz W	Duty Performance		Running Current 60 / 50 Hz Amp	Running Time 60 / 50 Hz Sec / 90°	Start Current 60 / 50 Hz Amp	Lock Current DC Amp
	Nm	in-lb			Cycles / hour	Starts / hour				
OM-1	35	310	10	40 / 50	30	240	0.4 / 0.4	15 / 15	2 / 2	1.8
OM-A / AM	50	445	10	40 / 40	30	240	0.3 / 0.3	24 / 24	2 / 2	1.8
OM-2	90	800	40	70 / 90	30	240	0.4 / 0.5	14 / 14	3 / 3	2.2
OM-3	150	1330	40	70 / 70	20	120	0.4 / 0.4	22 / 22	3 / 3	2.2
OM-H	300	2655	60	90 / 110	20	120	0.5 / 0.6	22 / 21	3 / 3	3.0
OM-4	400	3540	80	250 / 270	20	120	1.5 / 1.6	15 / 15	8 / 8	7.3
OM-5	500	4430	80	270 / 280	20	120	1.6 / 1.7	21 / 21	8 / 8	7.3
OM-6	650	5755	80	200 / 200	20	120	1.2 / 1.2	26 / 25	8 / 8	7.3
OM-7	1050	9300	120	220 / 220	10	60	1.3 / 1.3	43 / 42	7 / 7	7.4
OM-8	1500	13280	120	270 / 290	10	60	1.6 / 1.7	48 / 48	7 / 7	7.4
OM-9	2000	17710	180	250 / 270	10	60	1.5 / 1.6	60 / 58	9 / 9	10.1

- The running current is measured at max torque.

1.6 200VAC, Modulating Control, Class C

Model	Torque		Motor Power W	Power Consumption DC / 60 / 50 Hz W	Duty Performance	Running Current 60 / 50 Hz Amp	Running Time 60 / 50 Hz Sec / 90°	Start Current 60 / 50 Hz Amp	Lock Current DC Amp
	Nm	in-lb							
OM-1	35	310	10	50 / 50	1200	0.4 / 0.4	16 / 14	- *	1.8
OM-A / AM	50	445	10	40 / 40	1200	0.3 / 0.3	26 / 26	- *	1.8
OM-2	90	800	40	90 / 90	1200	0.5 / 0.5	15 / 15	3 / 3	2.2
OM-3	150	1330	40	70 / 70	600	0.4 / 0.4	23 / 22	3 / 3	2.2
OM-H	300	2655	60	110 / 110	600	0.6 / 0.6	22 / 22	3 / 3	3.0
OM-4	400	3540	80	230 / 250	600	1.4 / 1.5	15 / 15	8 / 8	7.3
OM-5	500	4430	80	270 / 270	600	1.6 / 1.6	21 / 20	8 / 8	7.3
OM-6	650	5755	80	240 / 250	600	1.4 / 1.5	25 / 25	8 / 8	7.3
OM-7	1050	9300	120	220 / 240	300	1.3 / 1.4	45 / 44	8 / 8	7.4
OM-8	1500	13280	120	270 / 290	300	1.6 / 1.7	48 / 47	8 / 7	7.4
OM-9	2000	17710	180	250 / 250	300	1.5 / 1.5	58 / 56	9 / 9	10.1

- The running current is measured at max torque.

※ Class A, Class B and Class C actuators, complying with EN ISO 22153 Standard.

※ Class A+ and Class B+ actuators with extended duty cycle controller.

* The start current of SY-H215101 is soft start mode, the start current is lower than running current.



SUN YEH ELECTRICAL IND. CO., LTD.

No.68, Ln. 854, Sec. 1, Shatian Rd., Dadu Dist.,
Taichung City 432, Taiwan
Tel: +886-4-26985666 Fax: +886-4-26983668
E-mail: service@sunyeh.com



www.sunyeh.com